ABC/MBC41 Series Cover Kit

Not For New Design Please refer to exact equivalent product series

ULP40-CK





Features

- Cover Kit for use with ABC/MBC41 Series
- Non-corrosive
- Easy assembly
- Low weight
- Fully safe
- Access for AC and DC connector


SPECIFICATIONS FOR COVER-41-XBC		
Derating Guidelines	ABC/MBC41 Series: Ambient > 50°C, derate by 50% to 70°C.	
Kit Contents	Mounting Base, Cover, Insulator, Fixing Screws	
Mechanical Dimensions	84.5 x 61.6 x 26.5 mm	
Cover and Base Material	EG (Zintec) /CRCA/GI 1.0 mm thick (Powder coating/ Passivation/ ED coating black)	
Marked	A: PCB MTG; B: COVER MTG; C: SYSTEM MTG	


All dimensions are in mm. General tolerance: +/-1.0





Γ	PARTS	DETAIL	QTY	LOCATION
1	COVER KIT BASE	SCREW,PNHD,M3×4MM	4 NOS	AT "A"
L		SCREW,PNHD,M3x6MM	1 NO	AT "D"
2	COVER KIT TOP COVER	SCREW,CSK M3x6MM,130DEG	2 NOS	AT "B"
3	INSULATOR MYLAR	TO BE PLACED UNDER THE PSU IN CK	1 NO	BETWEEN PCB & CK BASE
4	SYSTEM MTG (NOT SUPPLIED WITH COVER KIT)	SCREW THREAD M3x0.5 3.0 MM MAX.PENETRATION	2 NOS	AT "C"







Asia-Pacific +86 755 298 85888 **Europe, Middle East** +353 61 49 8941

North America +1 866 513 2839